



Image for guidance purposes.

## TECHNICALS SPECIFICATIONS

Model:

**RENTAL**

### AHR-850

Gen set composed of engine and alternator perfectly assembled and fitted in a practical tubular chasis, that is adding great strenght and versatility.

**STANDBY POWER (LTP):**

(LTP: "Limited Time Power" norma ISO 8528-1)

**8,5 kVA**

## Engine

<b>Make</b>	Honda
<b>Model</b>	GX-390
<b>Fuel</b>	Gasoline
<b>Start</b>	Recoil Start
<b>Cooling system</b>	Air

Mechanical effect power (kWm)	6
Diameter x stroke (mm)	88x64
Compresion ratio	8:1
Series regulator	M
No. cylinders	1
Displacement (cm³)	-
Fuel consumption 100% (L/H)	3,4
Oil tank capacity (L)	1,1
Máx. oil consumption (kg/h)	-
Battery recommended V/Ah	-
Fuel tank capacity (L)	6,1

## Alternator

Voltage (V)	400 / 230
Frequency (Hz)	50
R.p.m.	3000
No. poles	2
Protection degree IP	21
Insulation	H

\*Series regulator **M**: Mechanical.

### Genset general characteristics

Prime Power PRP (kVA/kW)	-
Standby power LTP (kVA)	8,5
Frequency (Hz)	50
R.p.m.	3000
Voltage (V)	400 / 230
Cos Φ	1

### Dimensions and weight

Dimensions (mm) Lenght x Width x Height	810x550x600
Weight (kg)	90

### OPTIONS

Lifting hook
Big fuel tank 21 liters
Transport handles kit with wheels
Control panel with running hours & voltmeter
Control panel equipped with DSE 3110 for remote start

### Sockets description:

- 1 TRIPHASE CEE SOCKET
- 1 SINGLE PHASE SCHUKO SOCKET 16 A and termic protections.