



Image for guidance purposes.

TECHNICALS SPECIFICATIONS

Model:

RENTAL

AHR-600

Gen set composed of engine and alternator perfectly assembled and fitted in a practical tubular chasis, that is adding great strenght and versatility.

STANDBY POWER (LTP):

(LTP: "Limited Time Power" norma ISO 8528-1)

5,5 kVA

Engine

Make	Honda
Model	GX-270
Fuel	Gasoline
Start	Recoil Start
Cooling system	Air

Mechanical effect power (kWm)	4,6
Diameter x stroke (mm)	77x58
Compresion ratio	8,2:1
Series regulator	M
No. cylinders	1
Displacement (cm³)	-
Fuel consumption 100% (L/H)	2,3
Oil tank capacity (L)	1,1
Máx. oil consumption (kg/h)	-
Battery recommended V/Ah	-
Fuel tank capacity (L)	5,3

Alternator

Voltage (V)	400 / 230
Frequency (Hz)	50
R.p.m.	3000
No. poles	2
Protection degree IP	21
Insulation	H

*Series regulator **M**: Mechanical.

Genset general characteristics

Prime Power PRP (kVA/kW)	-
Standby power LTP (kVA)	5,5
Frequency (Hz)	50
R.p.m.	3000
Voltage (V)	400 / 230
Cos Φ	1

Dimensions and weight

Dimensions (mm) Lenght x Width x Height	810x550x600
Weight (kg)	79

OPTIONS

Lifting hook
Big fuel tank 21 liters
Transport handles kit with wheels
Control panel with running hours & voltmeter
Control panel equipped with DSE 3110 for remote start

Sockets description:

- 1 TRIPHASE CEE SOCKET
- 1 SINGLE PHASE SCHUKO SOCKET 16 A and termic protections.